



SHM 118
Subharmonic Mixer narrowband 100 - 140 GHz
Part-No.: 02000036



Technical Specifications	
RF Frequency [GHz]	100 - 140
RF Port	WR8.0 (UG387/U)
LO Frequency [GHz]	50 - 70
LO Port	
LO Power [dBm]	3
IF Frequency	10 MHz - 20 GHz
IF Port	2.92 mm male/female
Conversion Loss (DSB)	4,5
Noise Temperature	450
Max. RF Power	0 dBm
Max. LO Power	10 dBm
Max. Case Temperature	+45 °C