



WTA 60-90
Waveguide Tunable Attenuator 60-90 GHz

Part-No.: 04700052



Technical Specifications

Frequency Range [GHz]	60 - 90
RF Port	WR12 (UG387/UM)
Attenuation Range [dB]	0 – 40
Max. Input Power [dBm]	+20
Insertion loss [typ. dB]	0.4
Tuning	Micrometer



Typical Performance

WTA-90

